


Product Description

Sirenza Microdevices' SGA-6489 is a high performance SiGe HBT MMIC Amplifier. A Darlington configuration featuring 1 micron emitters provides high F_T and excellent thermal performance. The heterojunction increases breakdown voltage and minimizes leakage current between junctions. Cancellation of emitter junction non-linearities results in higher suppression of intermodulation products. At 850 MHz and 75mA, the SGA-6489 typically provides +34 dBm output IP3, 20.1 dB of gain, and +20.7 dBm of 1dB compressed power using a single positive voltage supply. Only 2 DC-blocking capacitors, a bias resistor and an optional RF choke are required for operation.



SGA-6489

DC-3500 MHz, Cascadable SiGe HBT MMIC Amplifier



Product Features

- High Gain : 17.5 dB at 1950 MHz
- Cascadable 50 Ohm
- Patented SiGe Technology
- Operates From Single Supply
- Low Thermal Resistance Package

Applications

- PA Driver Amplifier
- Cellular, PCS, GSM, UMTS
- IF Amplifier
- Wireless Data, Satellite

Symbol	Parameter	Units	Frequency	Min.	Typ.	Max.	
G	Small Signal Gain	dB	850 MHz 1950 MHz 2400 MHz	18.4	20.1 17.5 16.5	22.4	
P _{1dB}	Output Power at 1dB Compression	dBm	850 MHz 1950 MHz		20.7 18.7		
OIP ₃	Output Third Order Intercept Point	dBm	850 MHz 1950 MHz		34.0 32.0		
Bandwidth	Determined by Return Loss (>10dB)	MHz			3500		
IRL	Input Return Loss	dB	1950 MHz		14.4		
ORL	Output Return Loss	dB	1950 MHz		10.9		
NF	Noise Figure	dB	1950 MHz		3.0		
V _D	Device Operating Voltage	V		4.7	5.1	5.5	
I _D	Device Operating Current	mA		67	75	83	
R _{TH, j-I}	Thermal Resistance (junction to lead)	°C/W			97		
Test Conditions:		V _s = 8 V R _{BIA} S = 39 Ohms	I _D = 75 mA Typ. T _L = 25°C	OIP ₃ Tone Spacing = 1 MHz, Pout per tone = 0 dBm Z _S = Z _L = 50 Ohms			


The information provided herein is believed to be reliable at press time. Sirenza Microdevices assumes no responsibility for inaccuracies or omissions. Sirenza Microdevices assumes no responsibility for the use of this information, and all such information shall be entirely at the user's own risk. Prices and specifications are subject to change without notice. No patent rights or licenses to any of the circuits described herein are implied or granted to any third party. Sirenza Microdevices does not authorize or warrant any Sirenza Microdevices product for use in life-support devices and/or systems. Copyright 2001 Sirenza Microdevices, Inc. All worldwide rights reserved.

Typical RF Performance at Key Operating Frequencies

Symbol	Parameter	Unit	Frequency (MHz)					
			100	500	850	1950	2400	3500
G	Small Signal Gain	dB	21.0	20.8	20.1	17.5	16.5	14.0
OIP ₃	Output Third Order Intercept Point	dBm	35.0	34.5	34.0	32.0	30.1	25.0
P _{1dB}	Output Power at 1dB Compression	dBm	20.6	20.9	20.7	18.7	17.4	14.0
IRL	Input Return Loss	dB	29.4	30.8	24.7	14.4	12.5	10.8
ORL	Output Return Loss	dB	18.7	16.3	14.6	10.9	10.9	10.0
S ₁₂	Reverse Isolation	dB	23.9	23.8	23.9	22.2	21.4	19.3
NF	Noise Figure	dB	3.2	2.8	2.7	3.0	3.4	4.4
Test Conditions: V _s = 8 V R _{BIAZ} = 39 Ohms			I _D = 75 mA Typ.	T _L = 25°C	OIP ₃ Tone Spacing = 1 MHz, Pout per tone = 0 dBm Z _s = Z _L = 50 Ohms			


Noise Figure vs. Frequency

V_D=5.1 V, I_D = 75 mA



OIP₃ vs. Frequency

V_D = 5.1 V, I_D = 75 mA



Absolute Maximum Ratings


Parameter	Absolute Limit
Max. Device Current (I _D)	150 mA
Max. Device Voltage (V _D)	7 V
Max. RF Input Power	+18 dBm
Max. Junction Temp. (T _J)	+150°C
Operating Temp. Range (T _L)	-40°C to +85°C
Max. Storage Temp.	+150°C







Operation of this device beyond any one of these limits may cause permanent damage. For reliable continuous operation, the device voltage and current must not exceed the maximum operating values specified in the table on page one.

Bias Conditions should also satisfy the following expression:
 $I_D V_D < (T_J - T_L) / R_{TH} j \cdot I$

P_{1dB} vs. Frequency



V_D = 5.1 V, I_D = 75 mA






* Note: In the applications circuit on page 4, R_{BIAS} compensates for voltage and current variation over temperature.

Basic Application Circuit



Part Identification Marking

The part will be marked with an "A64" designator on the top surface of the package.



Caution: ESD sensitive

Appropriate precautions in handling, packaging and testing devices must be observed.

Application Circuit Element Values

Reference Designator	Frequency (MHz)				
	500	850	1950	2400	3500
C _B	220 pF	100 pF	68 pF	56 pF	39 pF
C _D	100 pF	68 pF	22 pF	22 pF	15 pF
L _c	68 nH	33 nH	22 nH	18 nH	15 nH

Recommended Bias Resistor Values for I_D=75mA R_{BIA}S=(V_s-V_D)/I_D

Supply Voltage(V _s)	6 V	8 V	10 V	12 V
R _{BIA} S	12 Ω	39 Ω	62 Ω	91 Ω

Note: R_{BIA}S provides DC bias stability over temperature.


Mounting Instructions

1. Solder the copper pad on the backside of the device package to the ground plane.
2. Use a large ground pad area with many plated through-holes as shown.
3. We recommend 1 or 2 ounce copper. Measurement for this data sheet were made on a 31 mil thick FR-4 board with 1 ounce copper on both sides.

Pin #	Function	Description
1	RF IN	RF input pin. This pin requires the use of an external DC blocking capacitor chosen for the frequency of operation.
2, 4	GND	Connection to ground. For optimum RF performance, use via holes as close to ground leads as possible to reduce lead inductance.
3	RF OUT/BIAS	RF output and bias pin. DC voltage is present on this pin, therefore a DC blocking capacitor is necessary for proper operation.

Part Number Ordering Information

Part Number	Reel Size	Devices/Reel
SGA-6489	13"	3000



Nominal Package Dimensions

Dimensions in inches [millimeters]

Refer to package drawing posted at www.sirenza.com for tolerances.

